

Project:

Fixture Type:

Location:

Contact:

FRESNEL LENS

Ceiling chain or stem mounted • Damp location listed PROGRESS LED

Description:

The Fresnel one-light LED pendant has an antique-inspired Fresnel glass lens, industrial roots in form and function. 3000k, 90+ CRI 1,211 lumens.

Specifications:

- Brushed Nickel (-09) (plated)
- Steel construction
- Fresnel glass lens. glass lens
- 120VA replaceable LED Module (part # 93053641)
- Dimmable to 10% brightness (See Dimming Notes)
- + Canopy covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included
- 10 feet of wire supplied
- Two 6", one 12", two 15" lengths of stem included
- 9 gauge chain supplied
- ENERGY STAR[®] qualified

Performance:

Number of Modules	1
Input Power	17w
Input Voltage	120 V
Input Frequency	60 Hz
Lumens/LPW	1211/71.2 (LM-79)
ССТ	3000 K
CRI	90
Life (hours)	60,000 (L70/TM-21)
EMI/RFI	FCC Title 47, Part 15, Class B
Min. Start Temp	-30 °C
Max. Operating Temp	30 °C
Warranty	5 year warranty
Labels	cCSAus Damp location listed
	ENERGY STAR [®] qualified

P5188-0930K9

Images:



Dimensions:

Diameter: 12-1/8" Height: 10-1/2" Overall Ht. W/Stem: 76-1/2"



FRESNEL LENS

Ceiling chain or stem mounted • Damp location listed PROGRESS LED



P5188-0930K9

Dimming Notes:

P5188-0930K9 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron Diva DVELV-300P	
Lutron Nova T NTELV-300	
Luton Caseta	
Lutron Ariadni AY-600P	
Leviton Illumatech IPI06-1LZ	
Lutron Lumea LG-603PG	
Leviton SureSlide 6672	
Leviton SureSlide 6674	
Lutron Ariadni AYCL-153P	
Lutron Skylark Contour CTCL-153P	
Lutron Diva DVCL-153P	
Pass & Seymour Harmony DCL453PTCCCV6	
Lutron Toggler TGCL-153P	
Lutron Maestro MACL-153M	
Lutron Ariadni AYLV-600P	
Lutron Maestro MA-600	
Lutron NOVA T NTLV-600	
Lutron Maestro MAELV-600	
Lutron spacer/system SPSELV-600	
Lutron Renoir II AWRMG-EAW	

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.